

System Upgrades and Repairs

LIFEBOOK U7613

Version date	15.05.2023
Category	System Upgrades and Repairs
Version number	1.0
Classification	Non-classified - public

Contents

System Upgrades and Repairs	3
Information on the installation and removal of components	4
Screws	5
Tools	7
Switch off the battery	8
Remove the SIM card cover	9
Insert the SIM card cover	10
Remove the lower assy	11
Remove the battery	12
Insert the battery	13
Remove the memory door	15
Insert the memory cover	16
Remove the memory	17
Insert the memories	18
Remove the M.2 module	19
Insert the M.2 module	20
Mandatory Support Bulletins	21
Remove the WWAN module	22
Remove the protective foil	23
Remove the WLAN module	24
Remove the audio/USB/SD card sub board	25
Remove the fan	26
Remove the palm vein sensor / fingerprint sensor	27
Remove the speaker	29
Remove the touchpad buttons sub board	30
Remove the touchpad buttons	31
Remove the SmartCard reader	32
Remove the heatsink	33
Remove the CMOS battery	34
Remove the TPM module	35
Remove the keyboard	36
Insert the plastic strip of the keyboard	38
Remove the mainboard	39
Remove the LCD assy	40
Remove the upper assy	41

Remove the LCD hinge covers	42
Remove the LCD front cover	43
Remove the LCD hinges	44
Remove the LCD panel	45
LIFEBOOK U7613	48
Additional information LIFEBOOK U7613	50
Disposal information for recycling companies	51
Version history	53

System Upgrades and Repairs



We recommend printing out the relevant sections of this chapter prior to installation as the device for installing/removing hardware components needs to be switched off.

The following illustrations may differ from your device, depending on its configuration and features.

If you have received any further documents with your device, you should read these through carefully.

Please note the following instructions before installing/removing system components:



- The device must be switched off when installing/removing components and it must not be in power-saving mode.
- Disconnect the mains plug before opening the device.
- Press on the power button for approx. 5-10 seconds in order to discharge the remaining power.
- Remove all externally connected cables.
- Take care not to pinch any cables when installing/removing components.
- Please ensure that the installed components that might heat up intensely during operation do not exceed the permitted operating temperature.

Please take note of the target audience addressed in these instructions. Damage to the device incurred as a result of unqualified methods used during repair work as well as the use of unsuitable spare parts or assemblies during the repair work or upgrades of the device may void your warranty claim.



During a system expansion or a hardware upgrade, it is possible that the BIOS must be updated. You can find more information in the technical information provided for your device.

Information on the installation and removal of components

These instructions provide information on disassembling the device in addition to upgrading or exchanging components. The steps in these instructions describe the removal of a component. Installation is carried out in the reverse order. Specifics are separately described after the removal.

Please pay attention to the locking mechanism (indentations and centring pins) when installing hardware components.

Note that some components on the mainboard may be very hot if the device was in use shortly before the case was removed.

Utmost care is required during installation and removal to avoid damaging components.
Use a non-slip base.

Never use items with sharp edges (screwdrivers) to lever them out.

Parts with Electrostatic Sensitive Devices (ESD) can be identified by a corresponding label.

When dealing with boards with ESDs, the following points must always be observed:



- Always ensure there is a static discharge (e.g. by touching a grounded object) prior to commencing with the work.
- The devices and tools being used must not be statically charged.
- Only touch the components along the edges or on the areas marked in green (contact points).
- Contacts and electronic components must not touch when handling components equipped with ESD protection.

Screws

		 M2.5XL2.5
Screw: M2.5XL2.5 Screwdriver: Phillips PH00 (ISO 8764)		
		 M2.5XL6.5
Screw: M2.5XL6.5 Screwdriver: Phillips PH00 (ISO 8764)		
		 M2.0XL2.5
Screw: M2.0XL2.5 Screwdriver: Phillips PH00 (ISO 8764)		
		 M2XL4
Screw: M2XL4 Screwdriver: Phillips PH00 (ISO 8764)		
		 M2.5XL4
Screw: M2.5XL4 Screwdriver: Phillips PH00 (ISO 8764)		
		 M2 HSK
Screw: M2 HSK Screwdriver: Phillips PH 00 (ISO 8764)		

		 M2.5XL5
Screw: 2.5XL5 Screwdriver: Phillips PH 00 (ISO 8764)		
		 M2.0XL5.2
Screw: M2.0XL5.2 Screwdriver: Phillips PH00 (ISO 8764)		



Tools

Screwdriver: Phillips PH00 (ISO 8764)



Plastic tool (from iFixit: Part # 922-5065)



Plastic tool (from iFixit: Part # SKU: EU145335-1)



Tweezers (from iFixit: Part # SKU: EU145060-3)



Switch off the battery

Required work steps:

- Close the notebook
- Remove cables and components

Required tools:

- e.g. wire



- ▶ Press the battery reset button.



- ▶ The battery LED will temporarily flash red, then the battery will be switched off.



Remove the SIM card cover

Required work steps:

- Close the notebook
- Remove cables and components

Required tools:


- none



- ▶ Open the SIM card cover (1).



- ▶ Fully pull out the SIM card cover (2).



- ▶ Remove the SIM card cover (3).



Insert the SIM card cover

Required work steps:

- Close the notebook
- Remove cables and components
- [Remove the SIM card cover](#)

Required tools:

- none



- ▶ Slide the SIM card cover bracket (1) into the SIM tray opening (2).



- ▶ Close the SIM card cover (3).




Remove the lower assy

Required work steps:

- Close the notebook
- Remove cables and components
- [Switch off the battery](#)

Required tools:

- Screwdriver: Phillips PH00



- ▶ Undo the screws (1).
- ▶ Remove the lower assy (2).



Make sure the screws are tightly fastened and cannot be removed.

Remove the battery

Required work steps:


- [Switch off the battery](#)
- [Remove the lower assy](#)

Required tools:

- Screwdriver: Phillips PH00



The improper exchanging of the lithium battery can result in a danger of explosions!
The lithium battery may be replaced only by a battery recommended by the manufacturer.
Do not dispose of lithium batteries in the household waste. They must be disposed of in accordance with the local regulations, as hazardous waste.



- ▶ Undo the screws (1).
- ▶ Remove the battery (2).



Make sure the screws are tightly fastened and cannot be removed.


Insert the battery

Required work steps:


- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)

Required tools:

- Screwdriver: Phillips PH00



- ▶ Slide the battery in the direction of the arrow in the connector.



► Tighten the screws (1).



Once the battery has been replaced, the AC adapter needs to be connected to the device so the battery is once again ready for use.


Remove the memory door

Required work steps:


- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)

Required tools:

- Screwdriver: Phillips PH00



- ▶ Undo the screws (1)
- ▶ Remove the memory cover (2).



Make sure the screws are tightly fastened and cannot be removed.



[Return to Table of Contents](#)


Insert the memory cover

Required work steps:


- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)

Required tools:

- Screwdriver: Phillips PH00



- Tighten the screws (1).




Remove the memory

Required work steps:


- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)
- [Remove the memory door](#)

Required tools:


- none



- ▶ Press the latch in the direction of the arrow (1).



- ▶ Remove the memory (2).



 [Return to Table of Contents](#)





Insert the memory

Required work steps:

- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)
- [Remove the memory door](#)
- [Remove the memory](#)

Required tools:

- none



- ▶ Insert the memory into the socket (1).
- ▶ Due to mechanical coding, the module only fits into the socket (2) in one direction.
- ▶ Press the memory in the direction of the arrow until it snaps into place (3).



The module is initiated after insertion and the scroll lock LED will flash.



[Return to Table of Contents](#)



Remove the M.2 module

Required work steps:

- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)

Required tools:

- Screwdriver: Phillips PH00



- ▶ Remove the screw (1).
- ▶ Remove the module (2).





Insert the M.2 module

Required work steps:


- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)
- [Remove the M.2 module](#)

Required tools:

- Screwdriver: Phillips PH00



- ▶ Insert the module into the socket (1).
- ▶ Due to mechanical coding, the module only fits into the socket (2) in one direction.
- ▶ Tighten the screw (3).




Mandatory Support Bulletins



[SB-M-10030](#)

Minimum requirements to properly finalise hardware repairs on mobile systems



[SB-M-15007](#)

WIN8x & WIN10 - Spare product key for repaired devices



For any information about ESD, please refer to the web-based training course "[ESD in electronics](#)"



[SB-M-22005](#)

Creating a new Maintenance USB Stick FjAHDT.



[SB-M-22009](#)

Instructions for using the FjAHDT tool.


Remove the WWAN module

Required work steps:


- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)

Required tools:


- Screwdriver: Phillips PH00
- Plastic tool



(Example picture for 4G WWAN)




(Example picture for 5G WWAN)



- ▶ Remove the cables (1).
- ▶ Remove the screw (2).
- ▶ Remove the module (3)

Antenna colour	4G	5G
yellow	MAIN	MAIN
orange	AUX	AUX or D/G
white		M1
blue		M2




Remove the protective foil

Required work steps:

- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)

Required tools:

- none



- ▶ Remove the foil (1).



The foil is glued.



[Return to Table of Contents](#)

Remove the WLAN module

Required work steps:


- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)

Required tools:


- none



In the LIFEBOOK U7613, the WLAN module is soldered onto the mainboard and is therefore not replaceable. In case of repair in connection with the WLAN module, the mainboard must therefore be replaced.



- ▶ Remove the antenna cables.





Remove the audio/USB/SD card sub board

Required work steps:

- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)
- [Remove the protective foil](#)

Required tools:

- Screwdriver: Phillips PH00



- ▶ Open the connector locks and remove the cables (1).
- ▶ Remove the screw (2).
- ▶ Remove the sub board (3).




Remove the fan

Required work steps:



- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)
- [Remove the protective foil](#)

Required tools:

- Screwdriver: Phillips PH00



- ▶ Remove the cable (1).
- ▶ Remove the screws (2).




Remove the palm vein sensor / fingerprint sensor

Required work steps:


- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)

Required tools:

- Screwdriver: Phillips PH00




- ▶ Remove the screw from the finger print bracket (1).





- ▶ Remove the fingerprint bracket (2).
- ▶ Remove the cables (3).
- ▶ Remove the screw from the fingerprint sensor sub board (4).
- ▶ Remove the fingerprint sensor sub board (5).





- ▶ Remove the screws from the finger print bracket (6).
- ▶ Remove the fingerprint bracket (7).



- ▶ Remove the fingerprint sensor (8).



The LIFEBOOK may be equipped with a palm vein sensor or with a fingerprint sensor.



[Return to Table of Contents](#)


Remove the speaker

Required work steps:

- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)
- [Remove the M.2 module](#)

Required tools:

- none



- ▶ Remove the cable (1).
- ▶ Remove the adhesive tape (2).
- ▶ Remove the speaker (3).



Remove the touchpad buttons sub board

Required work steps:


- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)
- [Remove the M.2 module](#)

Required tools:

- Screwdriver: Phillips PH00



- ▶ Open the connector locks and remove the cables (1).
- ▶ Remove the screws (2).
- ▶ Remove the sub board (3).





Remove the touchpad buttons

Required work steps:

- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)
- [Remove the M.2 module](#)
- [Remove the touchpad buttons sub board](#)

Required tools:

- none



- ▶ Remove the cable from the guides (1).
- ▶ Remove the touchpad buttons (2).




Remove the SmartCard reader

Required work steps:


- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)

Required tools:

- Screwdriver: Phillips PH00
- Plastic tool



- ▶ Detach the plastic antenna bracket (1).
- ▶ Slide the bracket in the direction of the arrow (2).
- ▶ Lift the bracket (3).
- ▶ Remove the screw (4).
- ▶ Remove the SmartCard reader cover (5).
- ▶ Open the connector lock and remove the cable (6).
- ▶ Remove the sub board (7).




Remove the heatsink

Required work steps:


- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)
- [Remove the protective foil](#)

Required tools:

- Screwdriver: Phillips PH00



- ▶ Remove the screws (1).
- ▶ Remove the heatsink (2).



If necessary, replace the thermal grease when exchanging the heatsink.


Remove the CMOS battery

Required work steps:


- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)
- [Remove the protective foil](#)

Required tools:

- none



- ▶ Remove the cable (1).
- ▶ Remove the battery (2).



 The battery is glued to the mainboard.


Remove the TPM module

Required work steps:


- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)

Required tools:

- Screwdriver: Phillips PH00



- ▶ Remove the screw (1).
- ▶ Remove the module (2).




Remove the keyboard

Required work steps:


- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)

Required tools:


- Plastic tool



- ▶ Open the connector locks and remove the cables (1).
- ▶ Remove the adhesive tape from the cable (2).
- ▶ Press the latch in the direction of the arrow (3)
- ▶ Turn the device over.



- ▶ Lift the plastic strip (1).
- ▶ Slide the strip in the direction of the arrow (2, 3).
- ▶ Remove the plastic strip (4).



- ▶ Slide the keyboard in the direction of the arrow (5).
- ▶ Remove the keyboard (6).

Insert the plastic strip of the keyboard

Required work steps:


- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)
- [Remove the keyboard](#)

Required tools:

- none



- ▶ Route the plastic strip in the direction of the arrow into the intended openings (1).
- ▶ Route the plastic strip in the direction of the arrow into the intended openings (2).



- ▶ Push down on the plastic strip in the direction of the arrow until it locks into position (3).


Remove the mainboard

Required work steps:

- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)
- [Remove the memory door](#)
- [Remove the memory](#)
- [Remove the M.2 module](#)
- [Remove the WWAN module](#)
- [Remove the protective foil](#)
- [Remove the TPM module](#)
- [Remove the fan](#)

Required tools:


- Screwdriver: Phillips PH00
- Plastic tool



- ▶ Open the connector locks and remove the cables (1).
- ▶ Remove the screws (2).
- ▶ Remove the mainboard (3).



Please observe the information in [SB-M-22009](#).
The WLAN module is soldered onto the mainboard.



Remove the LCD assy

Required work steps:

- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)

Required tools:

- Screwdriver: Phillips PH00



- ▶ Remove the screws (1).
- ▶ Remove the cables (2).
- ▶ Open the connector lock and remove the cable (3).



- ▶ Lift the upper assy (4) until you can disconnect the LCD assy from the upper assy (5).


Remove the upper assy

Required work steps:

- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)
- [Remove the memory door](#)
- [Remove the memory](#)
- [Remove the M.2 module](#)
- [Remove the WWAN module](#)
- [Remove the protective foil](#)
- [Remove the TPM module](#)
- [Remove the fan](#)
- [Remove the mainboard](#)
- [Remove the palm vein/fingerprint sensor](#)
- [Remove the speaker](#)
- [Remove the touchpad buttons sub board](#)
- [Remove the touchpad buttons](#)
- [Remove the LCD assy](#)

Required tools:

- Screwdriver: Phillips PH00
- Plastic tool



The touchpad and the WWAN antennas are part of the upper assy.

Remove the LCD hinge covers

Required work steps:

- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)
- [Remove the LCD assy](#)

Required tools:

- none



- ▶ Remove the hinge covers in the direction of the arrow.




Remove the LCD front cover

Required work steps:

- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)
- [Remove the LCD assy](#)
- [Remove the LCD hinge covers](#)

Required tools:

- Plastic tool



- ▶ Start at the top left corner (1).
- ▶ Disconnect the screen covers from each other in the direction of the arrow (2, 3, 4, 5).
- ▶ On the left and right side, open the covers from the middle (3, 4).
Avoid applying pressure to the lower screen cover (red frame) to avoid damaging the



The LCD front cover is fixed in the area of the markings (6) on the LCD panel with double-sided adhesive tape. Be especially careful while disconnecting the screen covers to avoid damage.

Remove the LCD hinges

Required work steps:

- [Switch off the battery](#)
- [Remove the lower assy](#)
- [Remove the battery](#)
- [Remove the LCD assy](#)
- [Remove the LCD hinge covers](#)
- [Remove the LCD front cover](#)

Required tools:

- Screwdriver: Phillips PH00



- ▶ Remove the screws (1, 2).
- ▶ Remove the hinges (3).



Remove the LCD panel

Required work steps:

- [Switch off the battery](#)
- [Remove the upper assy](#)
-
- [Remove the battery](#)
- [Remove the LCD assy](#)
- [Remove the LCD hinge covers](#)
- [Remove the LCD front cover](#)

Required tools:



- Tweezers



The LCD panel is glued on both sides (1). Please see the instructions on how to remove the LCD panel on the next page.




- ▶ Turn the LCD assy so that the top side is facing you.




- ▶ Grab the tape and blue foil with tweezers (1).
- ▶ Carefully pull out the tape in the direction of the arrow (2).
- ▶ The tape can also be removed without the blue foil as shown in the examples (3, 4).


 To ensure that the adhesive tape does not tear, please pull it horizontally and keep holding it. If the tape breaks, the LCD panel cannot be removed.



► Remove the LCD panel (1).



⚠ Remove the remains of the tape. The camera and camera cable are part of the LCD back cover.



⚠ Pay attention to the microphone covers.

↑ [Return to Table of Contents](#)

Pos.	Spare part	Internal designation	Replaceable parts		Upgradeable	Repairable
			Customer	Service Partner		
	Mechanical parts:					
163	- Rubber foot		x			
178	- SIM slot cover	Depending on the device configuration	x			
165	- Memory door			x		
158	- Palm Vein bracket			x		
170/171	- Hinge cover			x		
174	- Hinges			x		
	Case:					
162	- Lower assy		x			
154	- Upper assy			x		
150	- LCD back cover			x		
152	- LCD front cover			x		
400	External AC adapter		x			
120	Battery		x			
90	Memory	Depending on the device configuration	x		x	
51	Storage media (SSD, M.2 module)	Depending on the device configuration	x		x	
	Cooling:					
13	- Heatsink			x		
176	- Fan			x		
10	Mainboard	Depending on the device configuration		x	x	x
71	WWAN module	Depending on the device configuration		x		
24	TPM module			x		
100	Palm Vein Sensor	Depending on the device configuration		x		
94	Fingerprint sensor	Depending on the device configuration		x		
60	LCD display	Depending on the device configuration		x	x	
130	Keyboard	Depending on the device configuration		x	x	
12	CMOS battery			x		
190	Speaker			x		
156	Touchpad buttons			x		
95, 23, 20, 22	Sub board (fingerprint sensor, USB/audio, touchpad, smart card)	Depending on the device configuration		x		
	Cables, flexprint cables, antennas	Depending on the device configuration		x		

	Touchpad: only if the upper assy is replaced					
	Webcam: To change it, replace the LCD back cover					
	Processor - only by replacing the mainboard					
	Graphics card: integrated in the main processor - only by replacing the mainboard					

Additional information LIFEBOOK U7613

Spare part availability:

5 years after end of product life

Spare parts can be obtained from our approved and certified service partners:

[Spare parts - Fujitsu Technical Support pages from Fujitsu EMEA](#)

The exploded diagram is available at the following link:

[Exploded diagram - Fujitsu Technical Support pages from Fujitsu EMEA](#)



Return to Table of Contents

Disposal information for recycling companies

These instructions are for the complete dismantling of a Fujitsu product. All materials can thereby be disposed of according to their provision in the EC directive 2012/19/EC (Waste Electrical and Electronic Equipment (WEEE)).

Product group: Mobile PC
Model: LIFEBOOK U7613

Materials which must be disposed of in a special manner		
Designation	Remarks	Quantity
Printed circuit boards with a surface area greater than 10 cm ²	Mainboard AC adapter LCD SSD Memory Touch Pad Depending on system configuration: WWAN Port replicator Mouse	1 1 1 1 1-2 1 1 1 1
Batteries	Lithium-ion battery - Method of attachment: Detachable - How to remove: Open the cover - Special tool for removal: None Lithium button batteries CR2032 - Included on the mainboard	1 1
Components containing mercury	Not contained	
Liquid crystal displays (if applicable, together with the casing) with a surface area greater than 100 square centimetres and backlit displays with gas discharge lamps	> 100cm ² display: Yes, for its display Gas discharge lamps: No	1
Cathode ray tubes	Not contained	
Capacitors containing PCBs (PolyChlorinated Biphenyls)	Not contained	
Electrolytic capacitors which contain critical substances (height > 25 mm; diameter: > 25 mm or proportional similar volumes).	Not contained	0
External electrical cables	AC adapter cable	1
Gas discharge lamps	Not contained	
Chlorofluorocarbons (CFC), hydrochlorofluorocarbons (HCFC) or hydrofluorocarbons (HFC), hydrocarbons (HC)	Not contained	

Materials which must be disposed of in a special manner		
Designation	Remarks	Quantity
Plastics which contain brominated flame retardant	<p>This product may contain plastic parts with Brominated flame retardants but to the best of our knowledge we provide this information to sort them out. Plastic parts location can be visually identified by their typical design function for the product (also shown in the disassembly manual).</p> <p>Many of these parts (Greater than 25 grams) are bromine free.</p> <p>Regardless, these parts are labeled (usually molded directly into the plastic) per ISO 11469. A typical label would look like:</p> <p>> Polymer Abbreviation - FR(xx) < i.e. > PC+ABS FR(40) <</p> <p>Flame retardant codes (FR(xx)) are given in ISO 1043-4. Codes for some Brominated flame retardants:</p> <p>14 aliphatic/alicyclic Brominated compounds 15 aliphatic/alicyclic Brominated compounds in combination with antimony compounds 16 aromatic Brominated compounds (excluding Brominated diphenyl ether and biphenyls) 17 aromatic Brominated compounds (excluding Brominated diphenyl ether and biphenyls) in combination with antimony compounds 22 aliphatic/alicyclic chlorinated and Brominated compounds 42 Brominated organic phosphorus compounds</p> <p>- Plastics parts weighing less than 25 grams may or may not contain brominated flame retardants. These smaller plastics parts may be found all over the PC system. It may especially include: fan, speaker.</p>	
Toner cartridges, liquid and paste-like, and colour toner	Not contained	
Asbestos waste and components which contain asbestos	Not contained	
Components which contain fire-proof ceramic fibres	Not contained	
Components which contain radioactive substances	Not contained	
Mass storage device(s)		
Does the product contain mass storage devices? If so, is any of them soldered to a circuit board?	Mass storage devices are contained, and they are not soldered to a circuit board.	1
Required tools		
Phillips Screwdriver		

Version history

Version	Date	Name	Change
1.0			