



★ ★ ★  
PROFESSIONAL



## SAT Multi Switch 9 → 8

This SCHWAIGER® multi switch is used to distribute digital signals of 2 satellite positions to up to 8 subscribers. Signals have to be fed from a Quattro LNB. All subscribers can make use of the entire range of programmes independently from one another. This multi

switch is solely supplied with power by the connected receivers. When no receiver is currently used, electricity usage of the multi switch and the connected LNB is 0 watts in sleep mode.



### ARTICLE INFORMATION

Article Nr SEW98 531  
EAN 4004005370324



Last updated: 24.07.2019



## FEATURES (SEW98 531)

- multi switch distributes 2 satellite positions to 8 outputs
- can be fed with terrestrial signals (passive)
- independent reception of all available programmes for every subscriber
- no power connection necessary
- very small size
- content: 1x SAT multiswitch, 4x screws

## TECHNICAL DATA

Quality	PROFESSIONAL
Colour	silver/blue
Connections (input)	8x F jack (SAT) 1x F jack (terrestrial)
Connections (output)	8x F jack (SAT)
Output level (max.)	97 dB $\mu$ V (SAT)
Frequency range	950 - 2150 MHz (SAT) 5 - 790 MHz (TV/FM)
Return loss	> 8 dB (input/output)
Tap loss	- 4 dB (SAT @ 950 MHz) + 2 dB (SAT @ 2150 MHz) - 18 dB (terrestrial 5 - 790 MHz)

Power consumption	through LNB 600 mA from the receiver: max. 30 mA
Operating temperature	-20 - +65 °C
Material of product	aluminium die cast
Dimensions (width)	155 mm
Dimensions (height)	80 mm
Dimensions (depth)	20 mm
Packaging	clamshell SF