

Terxon LX 8-Zone Wired Extension

Art. no. AZ4230

Page 1 of 1



- 5-wire bus connection
- 2 transistor outputs
- Enables individual identification of detectors (advisable in areas where safety and security are important)
- Allows clustering in logical areas
- Minimises cabling work

The Terxon LX 8-zone Wired Extension is an extension module for the Terxon LX. With this module you can extend your alarm system by 8 wired alarm zones. The 8 zones of the wired extension are connected to the motherboard of the Terxon LX via bus cables. You can connect up to 32 extension modules (wireless or wired) to your existing alarm control panel. The Terxon LX can thus be expanded to 264 zones. The additional alarm zones are freely programmable and monitored against tampering. The type of wiring – NC or DEOL – is left up to you, but it must be the same for all zones. You can address the zones of the extension module via jumper.

Technical Data:

Dimensions	(WxHxD) 128x183x35 mm
Connections	5-wire bus
Number of wired zones	8
Width	128 mm
Housing material	ABS
Height	183 mm
Length	35 mm
Power consumption	60 W
Max. operating temperature	55 °C

Max. humidity	96 %
Min. operating temperature	-10 °C
Net weight	0,31 kg
Tamper monitoring	Yes
Switching outputs	2
DC voltage supply	12 V
Power consumption	60 mA
Zone closure	NC, DEOL (FSL)