

Dear users:

Thank you for choosing Shenzhen ShuangMuSanLin Electronic Co., Ltd. M6 decoding amp. M6 decoding built-in USB, headphone amplifier in one (the decoding amp). M6 decoding amp uses an advanced design and superior materials from refined fever. Excellent workmanship, stylish appearance, simple operation, perfect sound quality. Will bring you a noble vision, auditory perception.

About this Manual:

This manual contains instructions apply to decode amp M6. Please read this manual before using the machine.

Precautions

Use headphones might not hear the sound of the external environment, for your personal safety, please do not use the headset in dangerous environments.


To protect your hearing, please insert in the state minimum volume of the headphone volume control using the machine in a comfortable situation.

Packing list

M6 : 1Pcs
The power adapter: 1Pcs
The manual: 1Pcs
USB cable: 1Pcs

6

Function:



A: Function keys

- + Push-up volume increase;
 - Push-down volume down;
 - ⊖ Push left to select the input source mode (USB, coaxial, fiber optic);
 - ⊕ Push right headphone, RCA outputs (Under the RCA outputs, volume control is not available);
 - ⏻ Long press to turn ON or OFF.
- B: Input source display.
C: Bit depth or sampling rate display.
Signal sampling rate display
D: Headphones volume display.

E: headphone output

Plug in your headphones to listen to music when using headphones into the headphone proposal in the state of minimum volume.

F:Right channel analog output

External amplifier

G:Left channel analog output

External amplifier

H:Coaxial input

Support 192KHz / 24Bit signal input

I :Optical input

Support 192KHz / 24Bit signal input

J :Computer USB input

K:DC power input(DC9V)

7

Warning:

To reduce the risk of fire or electric shock, do not expose the unit to get wet or damp.

Do not install the machine, such as a bookcase or closet narrow unventilated areas.

To prevent fire, do not let the vents newspapers, tablecloths, curtains, etc. to cover the device.

And do not place lighted candles on the apparatus and mosquito coils.

To prevent fire or shock hazard, not on the device, filled objects such as vases liquid.

Install this system so that you can immediately unplug the AC power cord from the wall outlet when a failure occurs.

Risk of electric shock Do not disassemble.

No internal repair parts, please consult a qualified repair person.

To prevent electric shock Do not disassemble the case, please consult a qualified repair person.

Indoor use only.

8

Specifications indicators:

USB Input: 16bit-32bit/ 32kHz-384kHz

Optical fiber, coaxial: 16bit-24bit; 32kHz-192kHz

Output level:2 Vrms

THD + N: <0.003%

Dynamic Range:> 115dB

SNR:> 120dB

Channel separation:> 110dB

Amp power: (@ 1% THD + N)

33Ω 130mW

66Ω 270mW

150Ω 220mW

300Ω 120mW

Amp distortion: 0.003% @10mW 300Ω

9

Warranty terms

1. The term of service

Shenzhen Shuangmu Sanlin Electronics Co.,LTD. promise good quality products, failure product from the date of sale under normal use within 7 days, the customer can choose to return or warranty (does not affect the secondary sales before they can return). Faulty for free within one year warranty normal use.

2. Date of purchase to the seller out of the purchase date of the invoice or receipt, online shopping can trade shots prevail.

3. Third, there is the following situation can not enjoy the "Three Guarantees" service:

- a. All damage to human factors, including the use of or not in accordance with the instructions to use the non-normal working environment.
- b. User privately disassemble, modification, maintenance;
- c. Use non-designated or approved accessories cause damage;
- d. fuselage QC or warranty stickers damage;
- e. can not produce a valid certificate purchase;
- f. Does not belong to the company's products.

4. How to warranty

This provision applies only to China, other countries in the region refer to the regulations of the local sales agents and national regulations.

10