

eNet wireless switching actuator or momentary-contact actuator, 2-gang Mini



| Specification | Order No. | Packing unit | £/piece without VAT | PS | EAN |
|---------------|-----------|--------------|------------------------|----|---------------|
| | 5425 00 | 1/5 | 114.88 | 02 | 4010337774228 |

Features

- The eNet wireless switching or momentary-contact actuator enables switching of lighting and motors.
- Operating modes: Switching actuator or momentary-contact actuator together for both outputs.
- Status feedback to eNet wireless transmitter.
- Scene operation.
- Operating mode buttons: Relay contact stays closed as long as telegrams are being received (max. 60 seconds).

Can be set with eNet server:

- Flashing function.
- Delay time.
- Switch-on/off delay.
- Switch-off pre-warning.
- Minimum switching repeat time.
- Permanent-on, permanent-off.
- Repeater function.

Can be set with eNet server:

- Localisation of the device.

Technical data

| | |
|------------------------------|--------------------|
| Rated voltage: | AC 230 V, 50/60 Hz |
| Standby: | max. 0.5 W |
| Ambient temperature: | -25 °C to +70 °C |
| Switching capacity AC 230 V: | 16 A / AC1 |
| Connected load | |
| - Light bulbs: | 2300 W |
| - HV halogen lamps: | 2000 W |
| - Wound transformer: | 1000 VA |

| | |
|-------------------------------------|-----------------|
| - Gira Tronic transformer: | 1500 W |
| - Fluorescent lamps, uncompensated: | 920 VA |
| - LED lamps: | typ. 500 W |
| - Compact fluorescent lamp: | typ. 500 W |
| - Motors: | 450 W |
| - Capacitive load: | 690 VA (560 µF) |

Connections: max. 4 mm²

Wireless frequency: 868.0 to 868.6 MHz

Range (free field): approx. 100 m

Notes

- Installation in device box, surface-mounted housing, or in an installation adapter.

Dimensions in mm

Ø 53 H 28