Terxon MX 8-Zone Wired Extension

Art. no. AZ4130



- 4-wire bus connection
- Enables individual identification of detectors (advisable in areas where safety and security are important)
- Allows clustering in logical areas
- Minimises cabling work

The Terxon MX 8-zone Wired Extension is an extension module for the Terxon MX. Using this module, you can extend your alarm system by up to 8 wired alarm zones. The 8 zones of the wired expansion are connected to the motherboard of the Terxon MX via 4-wire bus cables. You can connect up to 3 expansion modules (wireless or wired) to your existing alarm center. The Terxon MX can thus be expanded to up to 32 zones. The additional alarm zones are freely programmable and tampering-protected. The type of wiring – NC or DEOL – is left up to you, but it must be the same for all zones. Via a jumper on the circuit board, you can assign the zones of the expansion module (9 to 16, 17 to 24 and 25 to 32).

Technical Data:

Dimensions	(WxHxD) 128x183x35 mm
Connections	4-wire bus
Number of wired zones	8
Width	128 mm
Housing material	ABS
Height	183 mm
Length	35 mm

Power consumption	30 W
Net weight	0,33 kg
Tamper monitoring	Yes
DC voltage supply	12 V
Power consumption	30 mA
Certifications	REQ

Technical alterations reserved. Misprints and errors excepted. Copyright. © ABUS 01/2020