ALLNET MSR ALL3073V2WLAN



EAN CODE

4 0 3 8 8 1 6 0 9 0 2 8 7

Highlights:

- Enables the switching of the connected consumer (up to 16A) via the integrated web server- New Release 3.2
- Wireless LAN according to IEEE802.11b/g/n with 300 Mbps & 10/100 Mbit RJ45 network connection
- German earth contact plug/socket
- for 200 - 250 V alternating voltage
- Switching time, program controlled or manual possible

The ALL3073v2 network socket can be used to switch electrical devices on and off via a computer network. The ALL3073v2 acts as an intermediate plug between the power socket and the electrical consumer. It is integrated into a computer network and given a unique IP address. Configuration and operation are carried out independently of a specific platform or operating system via any web browser from PC, MAC, webpad or smartphone. Additional software is not required.

The switching operations can be programmed manually, time-controlled, etc.. Several ALL3073v2 can be switched in a network depending on each other. You can also work together with other ALLNET automation solutions, such as ALL369x Powermeter, ALL3418v2, ALL3500, ALL3505, ALL4500, or ALL5000.

The ALLNET ALL3073v2 adapter is also equipped with the heavily revised user interface 3.2. In addition to numerous innovations in the user interface, Release 3.2 for the first time also offers the possibility of integrating several ALLNET remote sensors and actuators into the control interface quickly and easily via JSON. The sensor data can thus be managed across locations via a central interface, which leads to significantly greater clarity and simpler administration.

In addition to the wired 10/100Mbit/s RJ45 network interface, the ALL3073v2 also has a wireless LAN interface

Errors and technical changes that serve the interests of progress or development of the product, are reserved.

according to the IEEE802.1b/g/n standard and can therefore also be integrated into a wireless LAN network; as a client or access point.

With the "Server Monitoring" function, you can cause the ALL3073v2 to monitor and reset a computer or router. A ping is sent to the registered system, if the system does not respond within a specified time, the output is turned off for a configurable time.

Application examples:

Targeted control and restart of PCs and servers from a distance
Remote restart of router incl. automatic startup (dead time programmable)
Time-controlled elimination of unnecessary power consumption by standby devices
Complex switching scenarios in connection with other ALLNET building automation products incl. influence of temperature, humidity, etc.
many other applications...

Technical data:

Network: 10BaseT,100BaseTX

Network connection:RJ45

Supported standards:IEEE 802.3, IEEE 802.3u

Protocols:HTTP/HTTPS, TCP/IP

Management / Control: via web browser, XML, JSON

Operating systems: all network-compatible operating systems

Voltage range: 200 - 250 Volt

Switching current: max. 16 Amps = 3680 resistive load

Housing: Plastic housing with integrated earth contact power socket/plug

environment: Temperature Operation: 0 ~ 40 °C
Humidity Operating: 10% ~ 85% (non-condensing)
Storage temperature: -20 ~ 60 °C
Humidity Storage: 5% ~ 90% (non-condensing)

Dimensions: 125 x 68 x 40 (60) mm (height x width x depth)

Weight: 200 gram (adapter only)

CE

Errors and technical changes that serve the interests of progress or development of the product, are reserved.



Accessories

Part No.	Name
146596	ALLNET MSR zbh. Signal/Warnlampe, Rot/Gelb/Grün/Buzzer einzeln ansteuerbar
126134	Crack-IT 785 Blitzlicht mit Schwellheuler AC 230V 100db / Gelb / IP43 / Alarmlicht
126135	Crack-IT 785 Blitzlicht mit Alarmsirene AC 230V 100db / Gelb IP43
134571	ALLNET MSR Zentrale "ALL3419" inkl. 3 Sensor Ports & WLAN & Temperaturfühler "ALL3006" für IP Gebäude Automation
98686	ALLNET MSR Zentrale "ALL3500" inkl. 4 Sensor Ports & WLAN für IP Gebäude Automation
101636	ALLNET MSR Zentrale "ALL3500PoE" inkl. 4 Sensor Ports & PoE & WLAN für IP Gebäude Automation
118725	ALLNET MSR Powermeter Zentrale "ALL3696" inkl. 1x S0 & 1x D0 & Induktion für IP Gebäude Automation
90325	\ALLNET Powermeter PM2 ALL3691 inkl. 1x 50A Phasenklemme
37038	ALLNET MSR ALL3088 / IP-Symcon Basic Software für ALL3000/ALL4000
96687	ALLNET MSR ALL3089 / IP-Symcon Prof. Software für ALL3000/ALL4000

ALLNET GmbH - Maistraße 2 - 82110 Germering - sales@allnet.de - 089 / 894 222 22

Errors and technical changes that serve the interests of progress or development of the product, are reserved.