

## Product Highlights

### Easy Expansion

Quickly add 7 additional USB 2.0 ports to any notebook or desktop computer, allowing you to connect more peripherals with ease

### Sync and Charge Your iPad or Tablets

Easily charge and sync your iPad and/or tablet at the same time, on any of the USB ports

### Compact and Portable

Slim profile allows it to fit easily into any bag for travel and can be used with or without a power adapter



## DUB-H7

# 7-Port USB 2.0 Hub

## Features

### Connectivity

- 7 x USB 2.0 ports
- Backwards compatible with USB 1.1

### Fast Charge Mode<sup>1</sup>

- 7 Fast Charge USB ports for high-power mobile devices such as an iPad or tablet
- Does not require a computer to charge devices

### Easy To Use

- Plug and play
- Sleek, compact design
- Works with Windows, Mac and Linux notebook or desktop computers

The D-Link DUB-H7 7-Port USB 2.0 Hub provides an easy way to add 7 additional USB ports to your PC or Mac, allowing you to connect more devices. With its Fast Charge Mode, each of the USB ports can provide sufficient power to connect and charge iPads and tablets.

## Add Four USB 2.0 Ports to Your Computer

With the DUB-H7 7-Port USB 2.0 Hub, you can conveniently add 7 additional USB 2.0 ports to a notebook or desktop computer, allowing you to connect 7 more USB devices, such as digital cameras, printers, external hard drives, keyboard/mouse, flash drives and tablets. USB 2.0 technology supports fast data transfer rates of up to 480 Mbps, which means that you can save/access files and sync your devices faster compared to previous USB standards.

## Fast Charge Your Devices

The DUB-H7 features 7 Fast Charge USB ports that are designed to provide increased maximum charging current of up to 2.4 A<sup>1</sup>. This makes it perfect for charging power-hungry devices like the iPad or tablets quickly, even with their high-capacity batteries.

## Compact and Portable

The DUB-H7 does not require to be connect to a computer to charge your devices. With it's compact size, so you can take it with you on your travels to charge your smartphone, tablet and camera without the need to bring multiple chargers. Alternatively, you can use the DUB-H7 without the power adapter to easily add 7 additional USB port to any computer.

## Plug and Play

Simply connect the DUB-H7 to your notebook or desktop computer to add 7 additional USB ports. It's that easy, no drivers or software installation required.

## Technical Specifications

### Standards

Standards	<ul style="list-style-type: none"> <li>• USB specification version 2.0 (data rates of up to 480 Mbps)</li> <li>• USB specification version 1.1 (data rates of up to 12 Mbps)</li> </ul>	<ul style="list-style-type: none"> <li>• OHCI</li> <li>• UHIC</li> <li>• EHCI</li> </ul>
Interfaces	<ul style="list-style-type: none"> <li>• Seven USB Type A (female) downstream ports, white</li> </ul>	<ul style="list-style-type: none"> <li>• Upstream USB Type B (female) port</li> </ul>
Connectivity Rules	<ul style="list-style-type: none"> <li>• Up to 127 devices</li> <li>• Up to 5 cascaded hubs</li> </ul>	
Minimum System Requirements	<ul style="list-style-type: none"> <li>• Windows 10 / 8 / 7 / Vista / XP</li> <li>• Mac OS X 10.3 or above</li> </ul>	<ul style="list-style-type: none"> <li>• Linux</li> </ul>
Power LED	<ul style="list-style-type: none"> <li>• Bus-powered (Blue):                             <ul style="list-style-type: none"> <li>• Standard Charge Mode</li> </ul> </li> </ul>	<ul style="list-style-type: none"> <li>• Self-powered (Green):                             <ul style="list-style-type: none"> <li>• Standard Charge Mode</li> <li>• Fast Charge Mode</li> </ul> </li> </ul>
Supplied Charging Current <sup>1</sup>	<ul style="list-style-type: none"> <li>• Standard Mode:                             <ul style="list-style-type: none"> <li>• 500 mA total for all seven front ports</li> </ul> </li> </ul>	<ul style="list-style-type: none"> <li>• Fast Charge Mode<sup>2</sup>:                             <ul style="list-style-type: none"> <li>• Max. 1.5 A each for Battery Charging 1.2 compliant devices</li> <li>• Max. 2.4 A each for iPad / iPhone</li> </ul> </li> </ul>
Power Input	<ul style="list-style-type: none"> <li>• 5V / 3 A DC</li> </ul>	
<b>General Specifications</b>		
Temperature	<ul style="list-style-type: none"> <li>• Operating: 0 to 40 °C (32 to 104 °F)</li> </ul>	<ul style="list-style-type: none"> <li>• Storage: -20 to 60 °C (-4 to 140 °F)</li> </ul>
Humidity	<ul style="list-style-type: none"> <li>• Operating: 10% to 90% non-condensing</li> </ul>	<ul style="list-style-type: none"> <li>• Storage: 5% to 95% non-condensing</li> </ul>
Dimensions (L x W x H)	<ul style="list-style-type: none"> <li>• 99 x 57 x 25 mm (3.90 x 2.24 x 0.98 inches)</li> </ul>	
Weight	<ul style="list-style-type: none"> <li>• 85 g (0.19 lbs)</li> </ul>	
Certifications	<ul style="list-style-type: none"> <li>• FCC</li> <li>• CE</li> <li>• C-Tick</li> </ul>	<ul style="list-style-type: none"> <li>• IC</li> <li>• RoHS</li> </ul>

<sup>1</sup> The total combined power draw must be under 2.4 A or 12 W.

<sup>2</sup> D-Link provides a Windows utility for simultaneously syncing and charging iPads with 30-pin connectors.



For more information: [www.dlink.com](http://www.dlink.com)

**D-Link European Headquarters.** D-Link (Europe) Ltd., D-Link House, Abbey Road, Park Royal, London, NW10 7BX. Specifications are subject to change without notice. D-Link is a registered trademark of D-Link Corporation and its overseas subsidiaries. All other trademarks belong to their respective owners. ©2016 D-Link Corporation. All rights reserved. E&OE.

Updated December 2016

**D-Link**<sup>®</sup>  
Home is where the **SMART** is