

Tap-radio® wireless pushbutton actuator dimming w/o N connection TF-TA65DL



TF-TA65DL

Tap-radio® wireless pushbutton actuator dimming w/o N connection

Wireless pushbutton actuator dimming without N connection. For single mounting 84x84x16/33 mm or mounting into the E-design switching system. Pure white glossy. With Power MOSFET. 230 V incandescent and halogen lamps up to 200 W, depending on ventilation conditions. Energy saving lamps ESL and 230 V LED lamps in 'trailing edge' mode up to 200 W or up to 40 W in 'leading edge' mode, depending on ventilation conditions. Min. load 20 W at 'trailing edge' mode and 8 W at 'leading edge' mode. No inductive (wound) transformers. With switching operation for children's rooms and snooze function. With integrated universal/direction pushbutton and terminals for additional wired pushbuttons. Power supply 230 V. Only 0.7 watt standby loss. Smart Home sensor and actuator.

Using easy tap-radio® technology, up to 24 wireless universal pushbuttons, wireless direction pushbuttons, wireless central control pushbuttons and motion sensors TF-BSB can be taught in. In addition the actuator can be locally controlled with a conventional 230 V wired pushbutton without glow lamp.

The integrated pushbutton works ex work as an universal pushbutton and can be taught-in as an direction pushbutton using the corresponding tap-radio tapping code.

Mounting over a 55 mm switch box. 16 mm over and 33 mm into the box. 230 V power supply and wired pushbutton terminals on the rear.



professional series

TF-TA65DL

Pushbutton actuator dimming

EAN 4010312318621

94,30 €/pc.