



☆☆☆
PROFESSIONAL



SAT Multi Switch 9 → 4

This SCHWAIGER® multi switch is used to distribute digital signals of 2 satellite positions to up to 4 subscribers. You can feed 2 Quattro LNBs as well as terrestrial signals. All subscribers can make use of the entire range of programmes independently from one

another. A special feature of this multi switch are the differently coloured connections to avoid mix-ups upon installation.



ARTICLE INFORMATION

Article Nr SEW4094 531
EAN 4004005409406



Last updated: 24.07.2019



FEATURES (SEW4094 531)

- multi switch distributes 2 satellite positions to 4 outputs
- can be fed with terrestrial signals (passive)
- independent reception of all available programmes for every subscriber
- content: 1x SAT multiswitch

TECHNICAL DATA

Quality	PROFESSIONAL	Transmission loss	(typ.) 0 dB (SAT) (typ.) 21 dB (TV/FM)
Colour	black/silver	Power supply	230 V AC
Point of use	indoor use	Power consumption	max. 60 W
Connections (input)	8x F jack (75 ohms) (SAT) 1x F jack (75 ohms) (TV / radio)	Operating temperature	-10 - 50 °C
Connections (output)	4x F jack (SAT)	Power supply unit	integrated
Output level (max.)	(typ.) 100 dB μ V (SAT) (typ.) 85 dB μ V (TV/FM)	Dimensions (width)	345 mm
Frequency range	950 - 2150 MHz (SAT) 47 - 862 MHz (TV/FM)	Dimensions (height)	120 mm
Control function	DiSeqC 2.0	Dimensions (depth)	60 mm
		Packaging	clamshell SF