

	<h2 style="margin: 0;">H310MHD PRO2 6.x</h2> <ul style="list-style-type: none"> • Supports 8th Generation Intel® Core™ Processor • Intel H310 single chip architecture • Support 2-DIMM DDR4-1866/ 2133/ 2400/ 2666 up to 32G maximum capacity • Support USB 3.1 Gen1 • Support HDMI display port • Support GbE LAN
--	---

Chipset	<ul style="list-style-type: none"> • Intel H310
CPU SUPPORT	<ul style="list-style-type: none"> • 8th Gen Intel® Core™ i7 LGA 1151 Processor • 8th Gen Intel® Core™ i5 LGA 1151 Processor • 8th Gen Intel® Core™ i3 LGA 1151 Processor • 8th Gen Intel® Pentium® LGA 1151 Processor • 8th Gen Intel® Celeron® LGA 1151 Processor • Maximum CPU TDP (Thermal Design Power) : 95Watt
MEMORY	<ul style="list-style-type: none"> • Support Dual Channel DDR4 1866/2133/2400/2666 MHz • 2 x DDR4 DIMM Memory Slot • Max. Supports up to 32GB Memory • Each DIMM supports non-ECC 4/8/16GB DDR4 module
INTEGRATED VIDEO	<ul style="list-style-type: none"> • By CPU model • Supports DX12 • Supports HDCP
STORAGE	<ul style="list-style-type: none"> • 4 x SATA3 Connectors • 1 x M.2 Key M Connector (10Gb/s) : Supports PCI-E SSD
LAN	<ul style="list-style-type: none"> • Realtek RTL8111H - 10/100/1000Mb/s Controller
CODEC	<ul style="list-style-type: none"> • Realtek ALC887 8-Channel HD Audio • Support HD Audio
USB	<ul style="list-style-type: none"> • 4 x USB 3.1 Gen1 Ports (2 on rear I/Os and 2 via internal header) • 6 x USB 2.0 Ports (4 on rear I/Os and 2 via internal header)
EXPANSION SLOT	<ul style="list-style-type: none"> • 1 x PCI-E 3.0 x16 Slot • 2 x PCI-E 2.0 x1 Slots
REAR I/O	<ul style="list-style-type: none"> • 1 x PS/2 Mouse • 1 x PS/2 Keyboard • 2 x USB 3.1 Gen1 Ports • 4 x USB 2.0 Ports • 1 x HDMI Connector, resolution up to 4096*2160@24Hz • 1 x DVI-D Connector, resolution up to 1920*1200@60Hz • 1 x VGA Port, resolution up to 1920*1200@60Hz • 1 x LAN port • 3 x Audio Jacks

INTERNAL I/O	<ul style="list-style-type: none"> • 1 x USB 3.1 Gen1 Header (each header support 2 USB 3.1(Gen1) ports) • 1 x USB 2.0 Header (each header supports 2 USB 2.0 ports) • 4 x SATA3 6Gb/s Connectors • 1 x Front Audio Header • 1 x Front Panel Header • 1 x CPU Fan Connector • 1 x System Fan Connector • 1 x 4-Pin Power Connector • 1 x 24-Pin Power Connector • 1 x Clear CMOS Header • 1 x COM Port Header
H/W MONITORING	<ul style="list-style-type: none"> • CPU / System Temperature Monitoring • CPU / System Fan Monitoring • Smart / Manual CPU Fan Control • System Voltage Monitoring
DIMENSION	<ul style="list-style-type: none"> • Micro ATX Form Factor Dimension: 22.8 cm x 17.7 cm (W x L)
OS SUPPORT	<ul style="list-style-type: none"> • Support Windows 10(64bit) • *Biosstar reserves the right to add or remove support for any OS with or without notice.
ACCESSORIES	<ul style="list-style-type: none"> • 2 x SATA Cable • 1 x I/O Shield • 1 x DVD Driver • 1 x Quick Guide

Audio+

<p>HD Audio</p> <p>Provides high quality sound with minimal loss of audio fidelity.</p>	
<p>AudioArt Capacitors</p> <p>PRO series comes with Nichicon high-end audio capacitors. Nichicon Capacitors offer artistic-like sound resolution and Hi-Fi audio amplification effect, making your room a live concert.</p>	

Video+

<p>DX12</p> <p>DirectX 12 introduces the next version of Direct3D, the graphics API at the heart of DirectX. Direct3D is one of the most critical pieces of a game or game engine, and we've redesigned it to be faster and more efficient than ever before. Direct3D 12 enables richer scenes, more objects, and full utilization of modern GPU hardware.</p>	
<p>Integrated HDMI with HDCP</p> <p>Onboard HDMI connector allows full video & audio support. It has industry-leading high definition video quality.</p>	

Speed+

<p>USB 3.1 Gen 1 Type-A</p> <p>Experience Fastest data transfers at 5 Gbps with USB 3.1 Gen 1--the new latest connectivity standard. Built to connect easily with next-generation components and peripherals, USB 3.1 Gen 1 transfers data 10X faster and backward compatible with previous USB 2.0 components.</p>	
<p>PCIe M.2</p> <p>PCIe M.2 32Gb/s is the latest storage interface, it delivers the highest bandwidth and lower latency. It's 3 times faster compared with PCIe M.2 10Gb/s.</p>	
<p>Charger Booster</p> <p>Charger booster is the best and efficient charger solution for apple devices such as iPad, iPhone. Basically, Charger booster Technology is able to boost the charging time to be more efficiency and faster once any apple goods connecting to our Motherboard. With charger booster technology, you are able to charge your apple devices up to 42 % faster.</p>	
<p>SATAIII 6Gbps</p> <p>SATAIII 6Gbps provides a higher bandwidth to retrieve and transfer HD media. With this super speed data transfer, SATAIII allows an incredible data boost which is 2x faster than the SATA 3G.</p>	
<p>Dual DDR4</p> <p>The primary advantages of DDR4 over DDR3, include higher module density, lower voltage requirements, coupled with higher data transfer rate.</p>	

Durable+

<p>Moistureproof PCB</p> <p>The popularity of PC usage and working environment is getting deteriorating and moist(rural, coastal, etc.). The PCB will be oxidizing easily by damp or absorbed moisture, and ionic migration or CAF (Conductive Anodic Filament) will be generated. Moisture-proof PCB meets high density and high reliability requirements for moisture proof.</p>	
<p>Low RdsOn P-Pak MOS</p> <p>Low resistance design can significantly reduce the current out of energy loss. Low temperature, small size, excellent thermal conductivity.</p>	
<p>Tough Power Enhanced</p> <p>To ensure the longevity of motherboard, PRO series with Tough Power Enhanced can endure massive electric current and ensure full energy output without additional energy loss, just like a super man protecting your PC system.</p>	

Protection+

<p>Super Anti-Surge Protection</p> <p>BIOSTAR exclusive Anti-Surge design provides the best protection of board and extends the product life. Having the latest model of "Transient Voltage Suppressor" on-board can effectively protect the board circuit, reducing the shocks caused by ESD as well as other damages arising from overvoltage transients to enhance system durability.</p>	
<p>Super LAN Surge Protection</p> <p>Super LAN Surge Protection, providing LAN port with more advanced antistatic protection capabilities by adding an integrated chip to strengthen electrical stability and prevent damage from lightning strikes and electrical surges. SLSP (Super LAN Surge Protection) series motherboard upgrades the existing system protection standards with maximum 4X protection comparing to other board makers.</p>	
<p>Nano Carbon Coating Heatsink</p> <p>Nano carbon coating heatsink enlarges the heat dissipation area to increase heat conductivity efficiently, compared to the aluminum-extruded heatsink.</p>	
<p>ESD Protection</p> <p>ESD (Electrostatic Discharge) is the major factor to destroy PC by electrical overstress(EOS) condition, ESD occurred by PC users when touch any devices connect to PC, which may result in damage to motherboard or parts .ESD protection is designed to protect the motherboard and equipment from damage by EOS</p>	
<p>OC / OV / OH Protection</p> <p>All BIOSTAR special circuit design detects overvoltage conditions and prevents voltage surges from spreading in real time. It also actively cuts off the overvoltage supply to protect your system. Over current protection, avoid motherboard from damage when doing overclock or an unusual current import. Over heat protection, avoid motherboard & CPU from burning when exceeding the temperature limitation.</p>	

DIY+

<p>UEFI BIOS</p> <p>Unified Extensible Firmware Interface (UEFI) is a brand new framework that provides a revolutionary interface. It is a modern clear and easy-to-use graphical user interface. The UEFI comes with a colorful easy-understand icons leads users into the setup layer directly.</p>	
<p>Header Zone</p> <p>Users can easily assemble their own computer, a simple-swap data discs and other accessories.</p>	

<p>BIO-Flasher</p> <p>Update BIOS effortlessly from a USB flash disk before entering the OS. BIO-Flasher is a convenient BIOS update tool. Just launch this tool and put the BIOS on USB pen driver before entering the OS. You can update your BIOS with only a few clicks without preparing an additional floppy disk or other complicated flash utility.</p>	
<p>eHot-Line Utility</p> <p>Integrated e-service automatically sends your technical support request to Biostar Globe tech support without any delay.</p>	
<p>BIOScreen Utility</p> <p>Personalize your desktop with customizable boot logo. BIOScreen is the new feature that lets you personalize and create your own style with unique, custom-made boot logo.</p>	

CPU-Chipset Features