

ENDRESS®

Power Generators

ESE 406 HS-GT

Order No. **112302**

Main features	
Alternator type	synchron
Max. Output 1~ [kVA/kW]	5.1/4.6
Continuous Power 1~ [kVA/kW]	4.2/3.9
Nominal voltage [V]	230
Nominal Current [A]	18,3
Power factor cos (phi)	0,9
Frequency [Hz]	50
Protection Class [IP]	23

Engine	
Engine Type	HONDA GX 270 / 8 HP
Design	1-cylinder 4-stroke OHV
Displacement [ccm]	270
Output 3000 rpm	4,6
CO2 emissions [g / kWh]	762
CO2 test procedure	k.A
Fuel	Petrol
Fuel tank capacity [l]	30
Fuel consumption @ 75% PRP [L/h]	1,6
Running time @ 75% PRP	18,8
Starting system	Recoil starterer
Sound power level LWA [db(A)]	97
Sound pressure level LPA (7 m) [db(A)]	72
Weight in kg ca.	61
Dimensions L x W x H [mm]	800 x 538 x 576
Shockproof sockets	2 x 230 V/16 A

This CO2 measurement results from testing over a fixed test cycle under laboratory conditions a(n) (parent) engine representative of the engine type (engine family) and shall not imply or express any guarantee of the performance of a particular engine'.

garantía alguna ni implícita ni expresa del rendimiento de un motor concreto.

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2021-9-27

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generators.de

A PART OF PRETTL

ESE 406 HS-GT

Order No. 112302

Equipment features
Lack of oil automatic switch-off
Alternator overload protection
HONDA + Briggs & Stratton OHV engines
Large fuel tank for long running times
Compound regulated high performance generators for 400 V

Possible applications	230V
Electric tools up to	3800W
Gardening or construction equipment up to	2600W
Compressors or pumps up to	2000W

Special equipment - not retrofittable	Order No.
RCD protection switch incl. earthing kit	162 009

Accessories	Order No.
Wheel kit	**161 000**
Maintenance kit	**164 029**

выразить любую гарантию работы конкретного двигателя.

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2021-9-27

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generators.de

A PART OF PRETTL