

ABUS Z-Wave Light Bulb

Art. no. SHLM10010

Page 1 of 2



- LED light bulb with warm white LED light (2700 K)
- As bright as a conventional 60 W light bulb with significantly lower power consumption
- Includes repeater function for extending the range of the Z-wave radio signal
- Fits in any E27 socket
- Voice control possible (depending on the Smart Home gateway)
- Integrated Z-wave radio chip for integration and control via your Smart Home gateway

The ABUS Z-Wave LED lamp can be an optical helper in many situations in your connected home. E.g. in case of danger, the escape routes can be perfectly illuminated by scene control. And if you are not at home, you can credibly simulate your presence by configuring scenarios. When it comes to comfort, you make no compromises compared to a 60W light bulb, with significantly lower power consumption.

The LED lamp produces warm white light (2700k), is dimmable and fits into any conventional E27 socket.

ABUS Z-Wave Light Bulb

Art. no. SHLM10010

Page 2 of 2

Technical Data:

Areas of usage	Inside
Colour temperature	2700 K
Color	White
Luminous Flux	806 lm
Lamp Life	25.000 h
Socket	E27
Colour rendering index (CRI)	80
Dimming levels	5 - 100 %
Energy efficiency class	A+
Repeater function	Yes
Dimming function	Yes
Compatible with Secvest	No
Compatible with Smartvest	No
Power consumption standby	0,5 W
Number switching cycles	100.000
Warm-up time	1 s
Power Factor	0,9
Min. humidity	10
Dimensions	(Ø x H) 60 x 120 mm

Horizontal/vertical IR angle	240 °
Gross weight	0,15 kg
Wireless modulation	Z-Wave Plus (S2) / FSK (BFSK / GFSK)
Radio frequency	868,42 MHz
Wireless range	(Depending on installation) 20 - 100 m
Housing material	PBT / PC
Power consumption	9 W
Luminous color	Warm white
Max. operating temperature	40 °C
Max. humidity	95 %
Min. operating temperature	-20 °C
Net weight	0,07 kg
Tamper protection	No
Transmission power	4,5 dBm
AC voltage supply	220 - 240 V