# Radio CXT® / LXT® / XGT®

# MR002GZ01

12V - 40V max

**With Bluetooth. Dual Power Sources: AC or Makita batteries.**

Sturdy radio and bluetooth speaker with IP65 protection rating. Can be used with 12V, 18V and 40V batteries or mains power. The device also has an AUX connection and a USB connector for charging the phone.Tool only, batteries are not included.




## Technical specifications

| | |
|---|---|
| CXT Battery | ✓ |
| Voltage LXT | ✓ |
| Voltage XGT | ✓ |
| Nominal Battery Voltage | 12 / 14,4 / 18 / 40 V |
| Speaker Output Power 12Vmax | 1,2 W (x2) |
| Speaker Output Power 18V | 3,5 W (x2) |
| Speaker Output Power 40Vmax | 5 W (x2) |
| Frequency Range AM | 522 - 1710 kHz |
| Frequency Range FM | 87,5 - 108 MHz |
| Continuous Use 14.4V / 3.0 Ah Battery | 10,5 h |
| Continuous Use 18V / 2.0 Ah Battery | 9 h |
| Continuous Use 18V / 3.0 Ah Battery | 17,5 h |
| Continuous Use 18V / 4.0 Ah Battery | 17,5 h |
| Continuous Use 18V / 5.0 Ah Battery | 23 h |
| Continuous Use 18V / 6.0 Ah Battery | 27,5 h |
| Continuous Use XGT® 40V Max / 4.0 Ah | 27,5 h |
| Product net weight | 4,3 kg |

## User benefits

- Compact and lightweight design
- IP65 rated for maximum weather and water resistance
- Compatible with CXT®, LXT®, XGT® batteries
- Bumpers and metal pipes protect against rough handling

## EAN 0088381739054

**Link to product - www.makitauk.com**

# Related products

## Standard AC

**SE00000678**
AC Adapter (UK)

## Optional AC

**SE00000678**
AC Adapter (UK)

## Other

**User manual**

**Parts drawing**