




47357114



## SCHUKO socket outlet with "ZSV" imprint enhanced contact protection, Berker K.1, orange

### Technical features

#### Architecture

|                   |                        |
|-------------------|------------------------|
| Design            | according to DIN 49440 |
| Technical version | Imprint "ZSV"          |

#### Main electrical features

|                 |          |
|-----------------|----------|
| Nominal voltage | 250 V    |
| Rated current   | 16 A     |
| Rated voltage   | 250 V AC |

#### Cover, door

- Central cover plate

#### Materials

|                       |                          |
|-----------------------|--------------------------|
| RAL colour            | RAL 2003 - Pastel orange |
| Colour of design line | orange                   |
| Colour                | orange                   |
| Colour                | orange                   |
| Material              | thermoplastic            |
| Surface appearance    | glossy                   |

#### Installation, mounting

- with clamp/screw fastening

#### Connection

|                          |                          |
|--------------------------|--------------------------|
| Connection terminals     | according to IEC 60884-1 |
| Connection terminals     | according to VDE 0620-1  |
| - with plug-in terminals |                          |

#### Use

- enhanced contact protection

#### Safety

|                                                |                          |
|------------------------------------------------|--------------------------|
| Protection index IP                            | IP20                     |
| IK protection code against mechanical impacts  | 05                       |
| Enhanced contact protection (child protection) | according to IEC 60884-1 |
| Enhanced contact protection (child protection) | according to VDE 0620-1  |
| - Enhanced contact protection                  |                          |

#### Identification

|                          |                        |
|--------------------------|------------------------|
| Main design line         | Berker K.1             |
| Secondary design line(s) | Berker K.5, Berker K.1 |

#### Instructions

- Insert colour-coded.