



SURPASSION *ST*



14
colors
backlight
effect



3 ZONE MULTICOLOR BACKLIGHT
20 MILLION CLICKS
32 BIT ARM PROCESSOR

BACKLIGHT ADJUSTMENT



ON THE FLY DPI / POLLING RATE ADJUSTMENT



- 3200 dpi-deadly precision with enhanced optical sensor
- 20 million clicks-ultra durable and long-lived switches
- On the fly dpi adjustment
- On-the-fly polling rate adjustment
- 32bit arm processor

SPECIFICATIONS

Product name SURPASSION ST Gaming Mouse
Sensor PixArt PMW3325 Optical gaming sensor
Resolution 800 / 400 / 1600 / 3200 DPI
Game type FPS / MMORPG / MOBA / RTS
Polling rate 125 / 250 / 500 / 1000Hz
Switching 20M gaming switches

Profile LED backlight 3 zone backlight
Maximum tracking speed 100 IPS
Maximum acceleration 20 G
Interface USB plug
Cable length 1.8m
Dimension 120(L) X 65(W) X 38(H) mm

M/N : CGR-SURPASSION ST

PACKAGE CONTAINS
SURPASSION ST Gaming Mouse
User Manual

SYSTEM REQUIREMENTS
Windows 10

