




286710



Tronic rotary dimmer 360 W (R, C) Light control, others

Technical features

Functions

- bulb-preserving soft startup

Main electrical features

Nominal voltage 230 V

Voltage

Operating voltage 230 V AC

Fuse

- short-circuit and overload proof (electronic fuse)

Power

Electronic transformers 20 ... 360 W

Materials

Colour not applicable

Material Plastic/metal

Dimensions

Axis dimension Ø 4 mm

Incandescent bulbs control

230 V incandescent lamps and halogen lamps 20 ... 360 W

Installation, mounting

- with spreader claws

Connection

Type of load capacitive

- with screw terminals

Equipment

- phase cut-off
- very low noise
- with change-over pressure switch

Safety

Halogen free yes

Identification

Application, usage Light control

Main design line Light control

Instructions

-
- Trouble-free operation will be obtained only with Berker TronicÂ® transformers.
-