Delock Adapter USB 3.0 > Displayport 1.2 (4K)

Description

Use this USB 3.0 to Displayport Adapter by Delock to connect additional monitors, LCD displays or projectors to a free USB 3.0 or USB 2.0 port of your PC or laptop. You can use up to 6 adapter on your computer and connect each additional monitor by one adapter. The adapter can mirror and extend the display and supports a resolution of up to 3840 x 2160. TV and video transmission will be displayed in Ultra HD (4K) quality.



Specification

- Connector:
  Input: 1 x USB 3.0 Type Micro-B female
  Output: 1 x Displayport 20 pin female
- Chipset: DisplayLink DL-5500
- Displayport 1.2 specification
- Transfer of audio signals
- Resolution up to 3840 x 2160 @ 30 Hz (depending on the monitor and your system)
- Supports 16 Bit and 32 Bit colour
- Up to 6 adapter per computer useable
- Integrated RAM 1 GB (DDR3 RAM)
- Setting: extended, mirrored, primary display
- Dimensions (LxWxH): ca. 76 x 44 x 14 mm
- Power consumption: ca. 370 mA
- Resolution (depending on your system of your PCs or laptop) e.g.:
  640 x 480
  720 x 480
  768 x 576
  800 x 480
  800 x 600
  832 x 642
  848 x 480
  1024 x 600
  1024 x 768
  1152 x 864
  1152 x 870
  1280 x 720
  1280 x 768
  1280 x 800
  1280 x 960
  1280 x 1024
  1360 x 768
  1366 x 768
  1368 x 768
  1400 x 1050
  1440 x 900
  1600 x 900
  1600 x 1200
  1680 x 1050
  1920 x 1080
  1920 x 1200
  2048 x 1080
  2048 x 1152
  2048 x 1280

Item No. 62581

EAN: 4043619625819

Country of origin: China

Package: Retail Box



© 2017 by Delock. All names and symbols mentioned here are property of the respective producer. Printing errors, changes and errors excepted.

2048 x 1536
2560 x 1440
2560 x 1600
3840 x 2160

System requirements

- Windows 7/7-64/8/8-64/8.1/8.1-64/10/10-64
- PC or laptop with one free USB 3.0 or USB 2.0 port
- When using 4K an appropriate monitor, PC and graphics card is needed

Package content

- USB 3.0 DP adapter
- USB 3.0 cable
- Driver CD
- User manual

Images







© 2017 by Delock. All names and symbols mentioned here are property of the respective producer. Printing errors, changes and errors excepted.