



PC CASES

MPG VIXTA 300R AIRFLOW PZ / W

FREE THE FLOW. COOLING UNLOCKED.



SPECIFICATIONS

Product Name	MPG VIXTA 300R AIRFLOW PZ / W
Case Form Factor	Mid-Tower
Motherboard Form Factor Support	Regular: ATX, Micro-ATX, Mini-ITX Back-connect: ATX, Micro-ATX
I/O Ports	1 x USB 20Gbs (Type-C) 2 x USB 5Gbs (Type-A) 1 x Audio-Out / Mic-in 1 x LED Button 1 x Power Button
Drive Mount Support	1 x 2.5" 1 x 2.5"/3.5" (select one)
Expansion Slots	7
Maximum GPU Length	390 mm / 15.35 inches
Maximum CPU Cooler Height	165 mm / 6.50 inches
Power Supply Support	ATX
Maximum PSU Length	up to 190 mm / 7.48 inches
Fan Size Support	Front: 2 x 160 mm Rear: 1 x 120 mm Top: 3 x 120 mm Side: 2 x 120 mm / 2 x 140 mm PSU Shroud: 3 x 120 mm
Pre-installed Fan Size	Front: 2 x 160 mm Rear: 1 x 120 mm
Pre-installed Fan Type	Front: 2 x ARGB Fan Rear: 1 x ARGB Fan
Radiator Size Support	Front: N/A Rear: 120 mm Top: 120 / 240 / 360 mm Side: 120 / 240 mm Bottom: N/A
Dimensions (DxWxH)	455 x 235 x 497 mm / 17.9 x 9.25 x 19.57 inches
Net Weight	8.79 kg / 19.38 lbs
Gross Weight	11.2 kg / 24.69 lbs

FEATURES



Floating Base Design

The elevated chassis design enhances bottom airflow while preserving the high-transparency panoramic look, perfectly blending style with cooling efficiency.



Simplified PSU Installation

The expanded PSU chamber provides ample space, making cable management effortless. Install your power supply directly from the rear without removing side panels.



1-to-4 ARGB&PWM Control Board

This fan control board supports up to 4 x ARGB fan function. Allow you to use the LED switch button to adjust the ARGB lighting intuitively.



Superior Cooling

Featuring a mesh front panel and 2 x pre-installed 160 mm fans, significantly boosts airflow. The unique one-piece pogo-pin connector makes removal and cleaning effortless.

CONNECTIONS



P C C A S E S

MPG VIXTA 300R AIRFLOW PZ / W

FREE THE FLOW. COOLING UNLOCKED.



1. Power Button
2. LED / Reset Switch Button
3. Mic In/ Audio Out
4. 1 x USB 20Gbps (Type-C)
5. 2 x USB 5Gbps (Type-A)