

**SCHUKO socket with clamp terminals**  
**red****Product Data Sheet**

|                                        |                              |
|----------------------------------------|------------------------------|
| With child-protection                  | Yes                          |
| Frequency                              | 50-60Hertz                   |
| Nominal voltage                        | 230Volt                      |
| Halogen free                           | Yes                          |
| Nominal current                        | 16Ampere                     |
| Model                                  | Protective contact (SCHUKO)  |
| Connection type                        | Plug clamp                   |
| Colour                                 | Red                          |
| Mounting method                        | Flush mounted (plaster)      |
| Type of fastening                      | Mounting with claw and screw |
| Material                               | Plastic                      |
| Material quality                       | Duroplast                    |
| Surface protection                     | Untreated                    |
| Suitable for degree of protection (IP) | IP20                         |

**SCHUKO socket with clamp terminals**  
**red**

Socket SCHUKO® STANDARD with plug-in terminals, LED control light and red socket  
2-pole, 16 A 250 V~, with green LED as a voltage indicator, 230 V~/1mA, LED lifetime approx. 10 years, for combinations, with red central  
plate and labeling field 7 x 44 mm  
same, with increased protection against electric shock and labeling field 7 x 44 mm

| Material No. | Article No.              | EAN-code      |
|--------------|--------------------------|---------------|
| 00788871     | D 80.6511.36 SI NA LED/4 | 4010105788877 |

---

**PEHA Elektro GmbH & Co.KG**

a Honeywell Company  
Daimlerstraße 4  
58553 HALVER  
DEUTSCHLAND

Tel.: 02353 9118 001  
Fax: 02353 9118 311  
mail: [peha@honeywell.com](mailto:peha@honeywell.com)  
[www.peha.de](http://www.peha.de)

Änderungen vorbehalten. © Honeywell PEHA