



MXR-40PRO

Order No.: 0200490

Price upon request

PRODUCTINFOS

Professional 4-channel audio mixer,

with DSP effect unit, integrated MP3 player and Bluetooth receiver.

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full-duplex USB port (allows for simultaneous recording and reproduction) for reproduction of digital audio data from a PC and for recording mixings onto a PC
- 2 mono input channels with gain control, 3-way equalizer and pan pot
- 1 stereo input channel with 3-way equalizer and balance control
- MP3 player
- USB interface
- Bluetooth receiver
- 16 different DSP effects
- Adjustable aux return input and FX send output
- +48 V phantom power, can be activated as required
- Adjustable headphone output
- Stereo LED level display

TECHNICAL SPECIFICATIONS

MXR-40PRO

Input channels	4
Number of mix/mono	2
No. of stereo	1
Mic input	0.6 mV, bal. 2 x XLR
Line input	80 mV (stereo), 1 x 6.3 mm jack L/R 7 mV (mono), 2 x 6.3 mm jack
Aux input	340 mV, 1 x 6.3 mm jack L/R
Master output	760 mV, 1 x 6.3 mm jack L/R
Effect send	9 V, 1 x 6.3 mm jack
Headphones	$\geq 8 \Omega$, 1 x 6.3 mm jack
USB	yes
Bluetooth	yes
Frequency range	20-20,000 Hz
THD	< 0.03%
S/N ratio	> 75 dBA
Equalizer bass	± 15 dB/80 Hz
Equalizer midrange	± 15 dB/2.5 kHz
Equalizer treble	± 15 dB/12 kHz
Phantom power	+48 V
Power supply	~ 230 V/50 Hz/15 VA
Mains voltage	~ 230 V
Mains frequency	50 Hz
Power consumption, operation	15 VA
Admiss. ambient temp.	0-40 °C
Width	282 mm
Height	93 mm
Depth	320 mm
Weight	2.7 kg