



Product Video Information



AIRFORCE Product Video



AIRFORCE Assembly Video



AIRFORCE Installation Video



Product Story

Try True DIY

Admit it, you love building things, especially PCs! So, if you're feeling exceptionally crafty and are up for a new type of PC build, InWin introduces this new chassis set called AIRFORCE! Build, assemble and display with this detailed, 19-piece modular gaming chassis. There's a great feeling from building a PC, but a more satisfying feeling is building your chassis too!

Specifications



InWin AIRFORCE Chassis

Model	AIRFORCE		
Model Number	IW-CS-AIRFORCE-WHI, IW-CS-AIRFORCE-BLA		
Colors	Justice White, Phantom Black		
Case Type	Mid Tower		
Materials	Tempered Glass, SECC, ABS		
M/B Compatibility	12" x 13" (305 x 330 mm) E-ATX, ATX, Micro-ATX, Mini-ITX		
Expansion Slots	8 x PCI-E		
Maximum Compatibility	VGA Card Length: 390mm CPU Heatsink Height: 170mm		
I/O Ports	1 x USB 3.1 Gen 2 Type-C 2 x USB 3.0 HD Audio		
Internal Drive Bays	4 x 2.5" 2 x 3.5"		
Thermal Solution Compatibility	Air Cooling Fans: Front: 3 x 120mm Top: 3 x 120mm Rear: 1 x 120mm (4 InWin AL120 Fans Included)		
	Water Cooling Radiator: Front: 1 x 360mm Top: 1 x 360mm		
* Number of fans pre-installed	may vary based on different regions.		
Power Supply Compatibility	y PSII: ATX12V- Length up to 180mm		
Product Dimensions (H x W x D)	528 x 270 x 537mm 20.7 x 10.6 x 21.1"		
Package Dimensions (H x W x D)	240 x 590 x 550mm 9.4 x 23.2 x 21.6"		
Net Weight	6.9 kg / 15.2 lbs.		
Gross Weight	11.2 kg / 24.7 lbs.		

^{*} InWin's products comply with RoHS regulations.

^{*} Specifications may vary based on different regions.

Specifications

FORGE,

InWin Luna AL120 Fans

Model	Luna AL120		
Quantity Included	Single Pack	Triple Pack	
Model Number	IW-FN-AL120-1PK	IW-FN-AL120-3PK	
Colors	Black		
Fan Size	120 x 120 x 25mm		
Materials	PC, PBT		
Rated Voltage	DC 12V		
Rated Power	3.96W		
Rated Current	0.33A		
ADD RGB Rated Voltage	DC 5V		
ADD RGB Rated Power	1.5W		
ADD RGB Rated Current	0.3A		
Speed Mode	PWM 400-1800 +/-10% RPM		
Air Flow	82.96 CFM		
Air Pressure	2.31mm/H2O		
LED	Addressable RGB		
Connector (Fan to Fan)	Non-Modular Cables		
Connector to M/B	4-Pin (PWM, 12V), 3-Pin (ARGB, 5V)		
Noise Level	25 dB(A) (Normal)		
Bearing Type	Long Lifespan Sleeve Bearing		
Net Weight	133g	399g	
Gross Weight	169g	484g	
Package Dimensions	185 x 125 x 30mm	185 x 125 x 82mm	
(L x W x H)	7.3 x 4.9 x 1.2"	7.3 x 4.9 x 3.2"	
Warranty	2 Years		


- *InWin's products comply with RoHS regulation.
- * Specifications may vary based on different regions.





Package Contents













Accessories Bag

a. S-1 Screws



x 50

b. S-2 Screws



x 5

c. Hexagon Head Screws



x 26

d. Motherboard Stand-offs



x 15

e. Motherboard Stand-off Socket



x 1

f. 2.5" HDD Screws



x 16

g. 3.5" HDD Screws



x 8

h. Cable Ties



i. Graphic Cards Holder



j. PCI-E Slot Brackets






Case Structure





Case Structure





	1	2.5″/3.5″ HDD Quick Release Drive Bay	
I	2	2.5" SSD Mounting Area	
	3	Power Supply Mounting Area	
	4	Front Fans/Radiator Mounting Area	
	5	Top Fans/Radiator Mounting Area	
I	6	Rear Fan Mounting Area	
	7	Motherboard Mounting Area	
	8	CPU Cooler Installation Cut-Out Hole	
	9	PCI-E Expansion Slots	
	10	Graphic Cards Holder Mounting Area	
	7 8 9	Rear Fan Mounting Area Motherboard Mounting Area CPU Cooler Installation Cut-Out Hole PCI-E Expansion Slots	


Installation Guide

- FORGE
- * Please follow the related chapters to assemble.
- * Please only use original provided accessories to avoid damage to the product.

1 Opening the Chassis



2 Motherboard Installation











Parts Required:
Motherboard Stand-Offs,
Motherboard Stand-Off Socket
Hexagon Head Screws






















4 Connection Cables

I/O Wires




HD Audio Header




PORT2_L BLUE 10
SENSE_SEND PURPLE 8
PORT2_R YELLOW 6
PORT1_R RED 4
PORT1_L GREEN 2




USB3.0 Header






USB 3.1 Type-C Header







5 Fan / Liquid Cooling Radiator Installation






Parts Required: Included Luna AL120 Fans

Fan Installation Instructions: https://youtu.be/_S_LLcqeOKI

6 2.5"/ 3.5" Drive Bays Installation







Parts Required: 2.5"/ 3.5" HDD Screws

7 Power Supply Installation





Parts Required: Hexagon Head Screws

8 Installation Complete





Parts Required:Cable Ties

Notices and Warranty



■ Notices

- 1. Please follow the user manual for installation guidelines.
- 2. When installing the computer components, please use antistatic precautions to prevent ESD (electrostatic discharge) damage. Failure to take the necessary precautions may result in injury to the installer and/or damage to the machine. Incorrect installation may burnout the motherboard and other system components.
- 3. To avoid any damages, please do not use this product for any other purpose than its intended use.
- 4. Any modifications may damage the product.
- 5. Please remove all internal devices before shipping or moving. (Including power supply, hard drives, motherboard, CPU, etc.)
- 6. When storing the case, please keep this product away from high temperatures. Keep away from machines such as heaters that might cause high temperatures.

■ Warranty

- 1. For more detailed warranty information, please visit the InWin retail website at www.in-win.com.
- 2. The actual product is subject to change without prior notice. In Win Development Inc. reserves the right to make final modifications.





CONTEMPORARY & INNOVATIVE
www.in-win.com



Copyright © 2021 In Win Development Inc. All Rights Reserved.