

AVerTV Satellite Trinity (A707)

The most complete functional 4-in-1 PCI-E card



“**AVerTV Satellite Trinity**” allows you to access free-to-air digital satellite TV, DVB-T, and analog TV and FM radio with stereo sound support on your PC.

AVerTV Satellite Trinity is shipped with a “Universal DVB” plug-in and the best MCE software encoder solution for Windows Media Center Edition (MCE), providing you to watch or record DVB-S, DVB-T, analog TV programs directly under “My TV” on XP and Vista platforms. Also, AVerMedia’s exclusive Vista MCE Video Gaming Plug-in and Video Quality Enhancement Plug-in can synchronize the video and audio of video games on Vista MCE and adjust the bright/contrast/saturation of the video quality, allowing users to build up a Home Theater PC with more versatile entertainment.

Thanks to the latest AVer MediaCenter, **AVerTV Satellite Trinity** can even support up to 1080i high definition DVB-S / DVB-T programs with H.264 or MPEG-2 formats. Furthermore, its dual-mode function allows you to watch or record DVB-S and analog TV (or DVB-T) at the same time.

In addition, **AVerTV Satellite Trinity** is supported by ProgDVB and MyTheatre DVB-S watching software, allowing you to enjoy the digital broadcast in your favorite choice of software. In addition to its advanced AVerMedia software, AVerTV DVB-S Trinity also gives you options to customize your DVB-S watching habit.

At a Glance

- Watch free-to-air digital satellite TV, Worldwide analog TV access, DVB-T, and FM Radio broadcasting with stereo sound support
- S-Video / Composite Video (RCA) input support
- Ready for HDTV H.264 / MPEG-2 formats in DVB-S and DVB-T modes
- MCE Software MPEG-2 encoder to be fully compliant with MCE platform
- MCE Video Gaming Plug-in Support
- MCE Video Quality Enhancement Plug-in Support
- Dual-mode function allows users to watch or record DVB-S and analog TV (or DVB-T) at the same time
- Recording videos by real-time H.264 format and playing on iPod.

Specifications

Input Signal

- 75Ω TV Antenna Input
- S-Video
- Composite (RCA)
- Audio L/R
- Remote Sensor

DVB-S Tuner

- Receiving frequency: 950~2150MHz tuning range
- QPSK and FEC
- Symbol rate/Sec: 1~45MHz
- Viterbi decoding: 1/2, 2/3, 3/4, 5/6, 6/7, 7/8
- Input Level: -84~ -20 dBm
- DiSEqC 1.1

Software Features – AVer MediaCenter



Your Personal Multimedia Control Center-AVer MediaCenter



A clean and simple way to enjoy TV from your sofa

The new 10-foot user's interface provides you a easy way to access all your PC based media via the easy-to-use remote control.



TV | Enjoy an easier way to watch and record TV programs, even watch multiple channels at the same time via an antenna, cable, or satellite TV signals.

Teletext overlays on the screen just like it would on your TV for convenient viewing



Video | It offers an intuitive way to view your video files and folders by date or by name, providing an interactive video playback experience.



FM Radio | Offering instant access to FM radio, allowing you to listen to live radio, record, and TimeShift whenever you want.

Easily customize your viewing experience

- Multiple TV Tuner Cards Support
- PIP / PAP Setting allows the viewing of multiple channels simultaneously
- Sequential Snapshot
- Customized Color Adjustment
- Media Files Management
- Complete Channel Scan Capability
- Record Videos in MPEG-1/2/4 Format

Expand your multimedia horizons!



Music: Easily access your personal digital music library, play it as background music while viewing the slideshow photos or using other functions on your computer.



Pictures: PC monitor is too small to share pictures with family and friends? AVer MediaCenter offers a fun new way to enjoy and share your digital photos with stylish slideshow effect.

PACKAGE INCLUDES

- AVerTV Satellite Trinity (Weight: 75g)
- Quick Guide
- Installation CD
- All-in-One Cable
- Audio Cable
- Infrared Sensor
- FM Cable
- Remote Control (Batteries included)

SYSTEM REQUIREMENTS

- For TimeShift and Record in MPEG-2
 - Pentium® 4 2.4GHz (Hyper-Threading)
 - AMD® AthlonXP® 2600+
- For HDTV (H.264) Previewing
 - Intel® Core™ 2 Duo 2.4 GHz or equivalent
- For H.264 Recording and TV on MCE platform
 - Pentium® 4 3.0GHz (Hyper-Threading) or equivalent
- 512 MB RAM or above
- VGA card supports DirectX 9.0c
- Satellite Dish
- Sound card
- PCI Express x1 Compatible Slot
- Windows® 7 / Vista / XP

Note: Please visit AVerMedia website for the most updated driver and application.

*(Only for Analog TV) To encode MPEG-4 format, we suggest that users should download DivX codec from www.divx.com or XviD codec from www.xvid.org. The codecs are not developed by AVerMedia. Therefore, AVerMedia could not guarantee the function of MPEG-4 recording.

AVerMedia's Quality Insistence

AVerMedia's products are not only commit to RoHS/WEEE Directive, but conduct EMI and safety countermeasure to ensure consumers' health and environment protection. All products are available with lead-free finishes and flame retardant.



AVerMedia